



SECURELY  
for living

## Product

**Bi-directional, compact Remote Control with advanced functions for Security purposes**

**Features include:**

- 5-button interface – Three arming modes (Full, Day, Night), disarm and status keys
- LED indications of system status
- Ability to force arming for open zone or tamper situations
- Compact, easy to carry design
- Personal SOS alarm (panic button)
- Remote deactivation, in case of loss or theft
- Easy battery insertion
- Efficient power consumption to extend the operation period

## SECURELY for living

**The SECURELY for living suite allows living life fully through smart connected homes**

- Home security, safety and home automation at the core
- Notifications of security events and remote management of the home in real time
- Modular and expandable - manage connected home devices with Z-Wave® expansion
- Smart Rule engine for automation – decide which device, condition, or event will trigger which actions and at what time
- Live HD video – anytime, on any screen
- Save energy and money by ensuring that lights and air conditioning are turned off when not at home

For more information go to <http://www.securely.nz>  
or call 0800 904 904

# Remote Control



NZLES800KF

Remote Control & Panic Button

## Specifications

### COMMUNICATION

- **Maximum RF Range:** 600 m open air
- **Maximum Transmission:** 25 mW (14 dBm)
- Proprietary bi-directional radio protocol
- **Modulation and Frequency:** DSSS, 2.4 GHz
- **Data Security:** 128 bit AES encryption

### POWER CONSUMPTION

- One 3V CR2450 lithium battery
- Three-year battery life

### DIMENSIONS

- **Size:** H: 12.3 mm, L: 87.3 mm, W: 61 mm
- **Weight:** 25 g including the battery

### ENVIRONMENT

- **Storage Ambient Temperature range:** -10°C – +55°C
- **Operating Ambient Temperature range with battery:** -5°C – +55°C
- **RF Operating Humidity:** Up to 95% non-condensing



SECURELY  
for living

Information contained within this document may change without notice.